



APG CASH DRAWER

PK-212-1 CABLE PINOUT GUIDE MODEL 212A SERIAL INTERFACE CASH DRAWER

212 Interface Cable Available in APG Kit No. PK-212-1

Note: the AUX Device connector included on the cash drawer cable to serve as a pin-to-pin extension of the serial port to provide support of a second parallel device on the same port as the drawer.

Connector #1-CashDrawer DB25(F)-malescrew	Connector #2-SerialPort DB25(F)-malescrew	Connector #3-AUXdevice DB25(M)-femalescrew lock
1	1	1
2	2	2
3	3	3
4	4	4
5	5	5
6	6	6
7	7	7
8	8	8
N/C	9	9
N/C	10	10
N/C	11	11
N/C	12	12
N/C	13	13
N/C	14	14
N/C	15	15
N/C	16	16
N/C	17	17
N/C	18	18
N/C	19	19
20	20	20
N/C	21	21
22	22	22
N/C	23	23
N/C	24	24
N/C	25	25
Shell	Shell	Shell

25 to 9 pin Serial Port Adapter Pinout

DB-25 Male Connector / Cash Drawer Side

2
3
4
5
6
7
8

DB-9 Female Connector / Connect to PC

3
2
7
8
6
5
1

20
22
Shell

4
9
Shell